

## DELO-DOT pilot 1i



## Cycle generator of DELO-DOT PN5

With the DELO-DOT pilot 1i cycle generator, the clock cycles, heating and feedback signals can be created or queried easily and with minimum programming effort. It can optionally be integrated into the control of the DELO-DOT PN5.

## **Technical data**

Operation of use	Switch cabinet
Dimensions	25 mm × 116.6 mm × 100 mm
Power supply	24 V (± 10 % max.)
Power consumption	100 W
Operating temperature	+15 °C to +45 °C
Interfaces	PLC I/O Interface RS232
Weight	120 g
Product compatibility	DELO-DRIVERBOX PN DELO-DOT PN5